Туре:	20KVA 3 Phase Diesel Generator
Brand:	FAW
Engine Model:	4DW81-23D
Fuel Consumption:	Fuel consumption 100% 5.8 L/H Fuel consumption 75% 3.8L/H Fuel consumption 50% 2.9L/H Fuel consumption 25% 1.4L/H
Engine Spec:	Displacement: 2.54L Cylinder bore/stroke: 90mm x 100mm Fuel system: In Line fuel Injection Pump Cylinders: 4 Cylinder arrangement: Vertical online Engine output power at 1500rpm: 21 KW Turbocharged or normally aspirated: Normally Aspirated Cycle: 4 Stroke Combustion system: Direct Injection Compression ratio: 17:1 Cooling method: Watercooled Governor system: Electronic Engine speed: 1500 RPM
Features and Benefits:	SmartGen controller with engine protection module DC Volt meter Oil Pressure Indication Water Temp sender control unit Electronic hour meter Fuel Gauge Running Amps on Load and Eskom per phase indicator Green and yellow Light Indicator - Eskom or Generator SmartGen 420 engine protection Module includes - High engine temp, Low oil Pressure ,Abnormal voltage, Start failure, Low fuel , Low battery Indication,overheating sending unit
How to order:	Kindly send us an email or give us a call. You can also request a quote through the wesbite