

Type:	150KVA 3 Phase Diesel Generator
Brand:	FAW
Engine Model:	CA6DF2-17D
Fuel Consumption:	<p>Fuel consumption 100% 26 L/H</p> <p>Fuel consumption 75% 19.8 L/H</p> <p>Fuel consumption 50% 14.8 L/H</p> <p>Fuel consumption 25% 9.7 L/H</p>
Engine Spec:	<p>Displacement: 6.55L</p> <p>Cylinder bore/stroke: 110mm x 115mm</p> <p>Fuel system: In Line fuel Injection Pump</p> <p>Cylinders: 6</p> <p>Cylinder arrangement: Vertical online</p> <p>Engine output power at 1500rpm: 125 KW</p> <p>Turbocharged or normally aspirated: Turbo Charged</p> <p>Cycle: 4 Stroke</p> <p>Combustion system: Direct Injection</p> <p>Compression ratio: 17:1</p> <p>Cooling method: Water-cooled</p> <p>Governor system: Electronic</p> <p>Engine speed: 1500 RPM</p>
Features and Benefits:	<p>SmartGen controller with engine protection module</p> <p>DC Volt meter</p> <p>Oil Pressure Indication</p> <p>Water Temp sender control unit</p> <p>Electronic hour meter</p> <p>Fuel Gauge</p> <p>Running Amps on Load and Eskom per phase indicator</p> <p>Green and yellow Light Indicator - Eskom or Generator</p> <p>SmartGen 420 engine protection Module includes - High engine temp, Low oil Pressure ,Abnormal voltage, Start failure, Low fuel , Low battery Indication,overheating sending unit</p>
How to order:	Kindly send us an email or give us a call. You can also request a quote through the wesbite